# **Panasonic**

### Super Dynamic Full HD Dome Network Camera

## WV-SFN631L

Super Dynamic HD Dome Network Camera
WV-SFN611L



# Full HD / 1,920 x 1,080 60 fps H.264 Network Camera featuring Super Dynamic (WV-SFN631L) HD / 1,280 x 720 60 fps H.264 Network Camera featuring Super Dynamic (WV-SFN611L)

### Key Features

- 1080p Full HD / 720p HD images up to 60 fps\*1
- Approximate 1/3 inches, high sensitivity MOS Sensor
- Super high resolution at Full HD/1,920 x 1,080 created by high sensitivity MOS Sensor. (WV-SFN631L only)
- Multiple H.264 (High profile) streams (max. 4 streams) and JPEG streams ensure simultaneous real time monitoring and high resolution recording by new enhanced "UniPhier®", Panasonic's proprietary System LSI platform.
- Maximum Screen Size is 2,048 x 1,536\* @30fps, H.264 (WV-SFN631L only)
   \* Used by super resolution techniques
- Enhanced Super Dynamic<sup>\*1</sup> and ABS (Adaptive Black Stretch) technologies deliver 133 dB wider dynamic range compared to conventional cameras.
- Multi process NR & 3D-DNR ensures noise reduction in various conditions.
- High sensitivity with Day & Night (IR) function:
   WV-SFN631L: 0.04 lx (Color), 0.01 lx (B/W) at F1.3
   WV-SFN611L: 0.01 lx (Color), 0.003 lx (B/W) at F1.3
- IR LED equipped: The equipped infrared LED makes it possible to take pictures at zero lx.
- IR LED is controlled to match the environment, thereby the camera provides clear images of human faces without white blur.
- New camera attachment bracket allows an easy camera installation toward all four directions.
- High Speed ABF (Auto Back Focus) and Motorized Zoom ensures easy installation.
- Newly developed lens with aperture control function realizes the best focus in any environment.
- VIQS (Variable Image Quality on Specified area) technology allows the designated eight areas to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- Cropping function enables to provide whole image and the part image simultaneously.
   Up to 4 image capture areas can be specified, and it is also possible to control the sequence.
- Face Super Dynamic technology ensures clear face image.
- Lens distortion compensation for the distorted images can be adjusted 256 steps.
- Electronic sensitivity enhancement: Auto (Up to 16/30s) / OFF
- Selectable light control modes:
  - Outdoor scene,Indoor scene (50 Hz) / Indoor scene (60 Hz),Fix shutter Indoor scene (50 Hz/60Hz): Flicker caused by fluorescent lightning will be automatically compensated.
- 3x (WV-SFN631L), 2x (WV-SFN611L) extra optical zoom at 640 x 360 resolution
- 2x, 4x digital zoom controlled by browser
- VMD (Video Motion Detection) with 4 programmable detection areas,
   15 steps sensitivity level and 10 steps detection size
- Privacy Zone can mask up to 8 private areas, such as house windows and entrances/exits.
- Camera title display: Up to 20 alphanumeric characters on the browser
- Alarm sources including 3 terminal input, VMD and Panasonic alarm command can trigger actions such as SDXC/SDHC/SD memory recording, FTP image transfer, E-mail notification, Indication on browser, Alarm terminal output, and Panasonic alarm protocol output.

- Full duplex bi-directional audio allows interactive communication between camera site and monitoring site.
- JPEG Image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- Double SDXC/SDHC/SD Memory card slots for manual recording (H.264 / JPEG), alarm recording (H.264 / JPEG) and backup upon network failure (H.264 / JPEG). Realize long-term recording and auto backup function.
- Newly developed dome cover provides clearer images above the horizontal.
   Thereby, it expands the tilting range of the lens.
- Face detection function detects the position of human face and the information is sent by XML or video stream.(Optional)
- Can be added new intelligent extension software(Optional) in addition to built-in VMD (Video Motion Detection), alarm function.
- Fog compensation function equipped as standard.
- HLC (High Light Compensation) technology reduces strong light sources such as vehicle headlights to prevent camera being blinded. (As of June 2014)
- Super Chroma Compensation function realizes a better color reproducibility even in low illumination.
- H.264 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Internet mode: H.264 images can be transmitted over HTTP protocol.
- Multi-language: English / Italian / French / German / Spanish / Portuguese / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- Onvif compliant model


\*1 Super Dynamic function is automatically set off on 60fps mode

# Optional Accessories Ceiling Mount Bracket WV-Q105A Ceiling Mount Bracket WV-Q174B Smoke Dome Cover WV-CF5SA WV-CF5SA


Camera	Image 9	Sensor	Approx. 1/3 type MOS image sensor
			WV-SFN631L: Approx. 2.4 mega pixels, WV-SFN611L: Approx. 1.3 mega pixel
	Effective Pixels Scanning Mode		Progressive scan
	Scannir	ng Area	WV-SFN631L: 5.346 mm (H) x 3.336 mm (V) {7/32 inches(H) x 1/8 inches(V)} WV-SFN611L: 4.864 mm (H) x 3.891 mm (V) {3/16 inches(H) x 5/32 inches(V)
	Minimu	m Illumination	WV-SFN631L: Color: less than 0.04 k, BW: 0.01 k (F1.3, Maximum shutter: Max. 1/30s, Gain: On(High)) Color: less than 0.003 k, BW 0.0007 k (F1.3, Maximum shutter: Max. 16/30s, Gain: On(High)) WV-SFN611L:
	IR LED Light		Color: less than 0.01 k, BW: 0.003 k, (F1.3, Maximum shutter: Max.: Off (1/30s), Gain: On(High)) Color: less than 0.0007 k, BW 0.0002 k, (F1.3, Maximum shutter: Max.: Max. 16/30s, Gain:On(High)) Off/Auto(High/Mid/Low)
		irradiation distance	Approx. 30 m {98.43 feet} AWC (2,000 ~ 10,000 K), ATW1 (2,700 ~ 6,000 K), ATW2 (2,000 ~ 6,000 K
	Light Control Mode		Outdoor scene: Automatic integration of ALC and ELC Indoor scene [50 Hz]: Automatic integration of ALC and ELC with flickerless Indoor scene [60 Hz]: Automatic integration of ALC and ELC with flickerless
	Shutter Speed		[2 mega pixel [16:9](60 fps mode)/ 1.3 mega pixel [16:9](60 fps mode)] OFF(1/60), 1/100, 1/120, 1/250, 1/500, 1/1000, 1/2000, 1/4000, 1/1000 Other than [2 mega pixel [16:9](60 fps mode)/ 1.3 mega pixel [16:9](60 fps mode) OFF(1/30), 3/100, 3/120, 2/100, 2/120, 1/100, 1/120, 1/500, 1/1000, 1/2000, 1/4000
	Super Dynamic*2 Face Super Dynamic		On(High) / On(Normal) / Off ON / OFF (Only at Super Dynamic : ON)
	Adaptive Black Stretch		ON / OFF (Only when Super Dynamic OFF)
	Fog compensation AGC		ON / OFF (Only when Super Dynamic / Adaptive black stretch: Off) ON (LOW, MID, HIGH) / OFF
	Electronic Sensitivity UP		To (LCW), MID, HIGH) / ORDOS, max. 1/500 s, max. 1/100 s, max. 1/100 s, max. 1/100 s, max. 1/30 s, max. 2/30 s, max. 4/30 s, max. 6/30 s, max. 10/30 s, max. 16/30 s
	Day & Night (IR)		1835 (1935), 1832
	Digital Noise Reduction		High / Low
	Video Motion Detection Privacy Zone		4 areas, Sensitivity: 15 steps, Detection size: 10 steps Up to 8 zones
	VIQS Camera Title (OSD)		Up to 8 zones Up to 20 characters (alphanumeric characters, marks)
	Electric Zoom		TELE / WIDE , Auto Coarse adjustment of Focus
		Adjustment stortion Compensation	ABF / MANUAL(Html only) 256 steps
Lens		cal Length	2.8 ~ 10mm {1/8 inches – 13/32 inches}
	Angular Field of View		WV-SFN631L [16:9 mode] Horizontal: 29.3° (TELE) - 104.1° (WIDE)  Vertical : 16.2° (TELE) - 56.8° (WIDE)  [4:3 mode] Horizontal: 24.0° (TELE) - 85.5° (WIDE)
			Vertical : 18.0° (TELE) - 63.3° (WIDE) WV-SFN611L [16:9 mode] Horizontal: 26.6° (TELE) - 95.1° (WIDE) Vertical : 14.9° (TELE) - 52.3° (WIDE) [4:3 mode] Horizontal: 26.7° (TELE) - 95.1° (WIDE)
	Maximum Aperture Ratio Focusing Range		Vertical : 20.0° (TELE) - 70.2° (WIDE)  1:1.3 (WIDE) ~ 1:3.0 (TELE) *with Smart DOF (Depth of Field) mode  0.3 m ~ ∞
Adjustin		ig i larige	Horizontal: ± 180°, Vertical: 0-85°, Image tilt adjustment range: -45°(Left) to +300°(Righ
Browser		ng	H.264(1) / H.264(2) / H.264(3) / H.264(4) / H.264(all) / JPEG(1) / JPEG(2) / JPEG(3)
GUI	Camera Control		Up to 4 image capture areas can be specified Brightness, AUX ON / OFF
	Display Mode  Digital Zoom		Spot, Quad: Image from 16 cameras can be displayed in 4 different Quac screens or 16 split screen (JPEG only). 20 characters camera title available 1x, 2x, 4x controlled by browser GUI
	Camera Title Clock Display		Up to 20 alphanumeric characters Time: 12H/24H, Date: 5 formats on the browser, Summer time (Manual)
	Alarm Control		Reset
	One Shot Capture Audio		A still picture will be displayed on a newly opened window.  Mic (Line) Input: ON / OFF Volume adjustment: Low / Middle / High,  Audio Output: ON / OFF Volume adjustment: Low / Middle / High
	SD Memory Data Download GUI / Setup Menu Language System Log		Still or motion Images recorded in the SDXC/SDHC/SD memory card can be downloade English, Italian, French, German, Spanish, Portuguese, Russian, Chinese, Japanese Up to 100 (Internal)
	Supported OS *3		
			Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista®
Notwork	Suppor	ted Browser	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Windows® Internet Explorer® 8.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit)
Network	Suppor	ted Browser  IF Image Capture Mode:	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector  WV-SFN631L:
Network	Suppor	ted Browser  IF Image Capture Mode: 2 mega pixel [16:9] (30/60 fps) Image Capture Mode:	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit) Mindows® Internet Explorer® 7.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L:
Network	Suppor	ted Browser  IF Image Capture Mode: 2 mega pixel [16:9] (00/60 fps) Image Capture Mode: 2 mega pixel [4:3] (30/fps) Image Capture Mode: 2 mega pixel [4:3] (30/fps)	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Windows® Internet Explorer® 7.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,080 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 wV-SFN631L:
Network	Support Network Image	IF Image Capture Mode: 2 mega pixel [163] (3010 b)s Image Capture Mode: 2 mega pixel [4:3] (301ps) Image Capture Mode: 3 mega pixel [4:3] (301ps) Image Capture Mode:	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Windows® Internet Explorer® 9.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 / 120 d y super resolution techniques WV-SFN611L:
Network	Support Network Image	IF Image Capture Mode: 2 mega pixel [16:9] (30:00 ft)s, Image Capture Mode: 2 mega pixel [4:3] (30fps) Image Capture Mode: 3 mega pixel [4:3] (30fps) Image Capture Mode: 1.3 mega pixel [6:3] (30tps) Image Capture Mode: 1.3 mega pixel [6:4] (30tps)	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Wista® Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) (108ase-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 1,204 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90
Network	Support Network Image	IF Image Capture Mode: 2 mega pixel [163] (30/60/15a) Image Capture Mode: 2 mega pixel [4:3] (30/fps) Image Capture Mode: 3 mega pixel [4:3] (30/fps) Image Capture Mode: 1.3 mega pixel [4:3] (30/fps) Image Capture Mode: 1.3 mega pixel [4:3] (30/fps) Transmission Mode Frame Rate	WV-SFN631L:  1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L:  1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L:  2,048 x 1,538 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 "Used by super resolution techniques WV-SFN611L:  1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L:  1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 Constant bitrate / Framerate priority / Best effort / Advanced VBR
Network	Support Network Image	ted Browser  IF Image Capture Mode: 2 mega pixel [16:3] (30%0 fps) Image Capture Mode: 2 mega pixel [4:3] (30fps) Image Capture Mode: 3 mega pixel [4:3] (30fps) Image Capture Mode: 13 mega pixel [4:3] (30fps) Image Capture Mode: 13 mega pixel [4:3] (30fps) Image Capture Mode: 13 mega pixel [4:3] (30fps) Transmission Mode Frame Rate Bit Rate/Client	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explore® 10.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,0080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,000 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536* / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 Constant bitrate / Framerate priority / Best effort / Advanced VBR 1 / 3 / 5 / 7 .5 / 10 / 12 / 15 / 20 / 30 / 60 fps 64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 / 4,096 / 6,144 / 8,192 / 10,240 / 12,288 / 14,336 / 16,384 / 20,480 / 24,576 kbps
Network	Suppor Network Image Resolution	ted Browser  IF Image Capture Mode: 2 mega pixel [16:3] (30/60 fps) Image Capture Mode: 2 mega pixel [4:3] (30/fps) Image Capture Mode: 13 mega pixel [4:3] (30/fps) Image Capture Mode: Image Capture Mode Image Quality Refresh interval	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explore® 10.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 Used by super resolution techniques WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 120 x
Network	Network Image Resolution H.264	IF Image Capture Mode: 2 mega pixel [163] (3016) [as] Image Capture Mode: 2 mega pixel [4:3] (3015) Image Capture Mode: 3 mega pixel [4:3] (3015) Image Capture Mode: 13 mega pixel [4:3] (3015) Image Capture Mode: 1.3 mega pixel [4:3] (3015) Image Capture Mode: 1.3 mega pixel [4:3] (3015) Iransmission Mode Frame Rate Bit Rate/Client Image Quality Refresh interval Transmission Type Image Quality	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit) Mindows® Internet Explore® 9.0 (32 bit) Mindows® Internet Explore® 9.0 (32 bit) 108ase-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 UV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 UV-SFN611L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 UV-SFN615 / 17 / 12 / 15 / 15 / 20 / 30 / 60 fps 64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 / 4,096 / 6,144 / 8,192 / 10,240 / 12,288 / 14,336 / 16,384 / 20,480 / 24,576 kbps LOW / NORIMAL / FINE D.2 / 10 x 100 x 1
Network	Suppor Network Image Resolution	ted Browser  IF  Image Capture Mode: 2 mega pixel [16:3] (3050 fps) Image Capture Mode: 2 mega pixel [4:3] (30fps) Image Capture Mode: 3 mega pixel [4:3] (30fps) Image Capture Mode: 13 mega pixel [4:3] (30fps) Image Capture Mode Image Quality Image Quality Refresh interval	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Mindows® Internet Explorer® 9.0 (32 bit) 10Base-T/ 100Base-TX, RJ-45 connector  WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90  WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  WV-SFN631L: 1,280 x 950 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  WV-SFN611L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  WV-SFN611L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  Constant bitrate / Framerate priority / Best effort / Advanced VBR  1/3 / 5 / 7.5 / 10 / 12 / 15 / 20 / 30 / 60 fps  64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 / 4,096 / 6,144 / 8,192 / 10,240 / 12,288 / 13,380 / 16,384 / 20,480 / 24,576 kbps  LOW / NORMAL / FINE 0,2 / 0,25 / 0,33 / 0,57 / 1 / 2 / 3 / 4 / 5s  UNICAST / MULTICAST 10 steps 0.1 fps - 30 fps (UPEG frame rate will be restricted when displaying both JPEG and H.264 images)
Network	Network  Image Resolution  H.264  '4	IF Image Capture Mode: 2 mega pixel [163] (3016) [as] Image Capture Mode: 2 mega pixel [4:3] (3015) Image Capture Mode: 3 mega pixel [4:3] (3015) Image Capture Mode: 13 mega pixel [4:3] (3015) Image Capture Mode: 1.3 mega pixel [4:3] (3015) Image Capture Mode: 1.3 mega pixel [4:3] (3015) Iransmission Mode Frame Rate Bit Rate/Client Image Quality Refresh interval Transmission Type Image Quality	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explore® 10.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 120 WV-SFN631L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 120 WV-SFN631L: 1,280 x
Network	Network  Image Resolution  H.264  4  JPEG  Audio C Audio N	IF Image Capture Mode: 2 mega pixel [16:3] (30/60 fps) Image Capture Mode: 2 mega pixel [4:3] (30/60), Image Capture Mode: 2 mega pixel [4:3] (30/fps) Image Capture Mode: 13 mega pixel [4:3] (30/fps) Image Capture Mode Image Capture Mode Frame Rate Bit Rate/Client Image Quality Image Quality Refresh interval Transmission Type Image Quality Transmission Type Ompression Mode	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Mindows® Internet Explorer® 9.0 (32 bit) 10Base-T/ 100Base-TX, RJ-45 connector  WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90  WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  WV-SFN631L: 1,204 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120  US-SFN631L: 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240
Network	Network  Image Resolution  H.264  4  JPEG  Audio C Audio N	ted Browser  IF Image Capture Mode: 2 mega pixel [16:3] (30/80 fps) Image Capture Mode: 2 mega pixel [4:3] (30/9s) Image Capture Mode: 3 mega pixel [4:3] (30/9s) Image Capture Mode: 13 mega pixel [4:3] (30/9s) Image Capture Mode: 13 mega pixel [4:3] (30/9s) Image Capture Mode: 13 mega pixel [4:3] (30/9s) Image Capture Mode 13 mega pixel [4:3] (30/9s) Transmission Mode Frame Rate Bit Rate/Cilient Image Quality Refresh interval Transmission Type Image Quality Refresh interval Transmission Type Compression Mode India Marchael Image Capture Image	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista® Windows® Internet Explore® 10.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit), Windows® Internet Explore® 9.0 (32 bit) 10Base-T / 100Base-TX, RJ-45 connector WV-SFN631L: 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN631L: 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 WV-SFN631L: 2,048 x 1,536 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 Used by super resolution techniques WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 120 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 120 WV-SFN611L: 1,280 x 720 / 640 x 360 / 320

Network	FTP Client	Alarm image transmission, FTP periodic transmission (When the FTP transmission
		is failed, backup on an optional SDXC/SDHC/SD memory card is available.)
	No. of Simultaneous Users	Up to 14 users (Depends on network conditions)
	SDXC/SDHC/SD	H.264 recording : Manual REC / Alarm REC (Pre/Post) / Schedule REC/
	Memory Card (Option)	Backup upon network failure Compatible (JPEG only)
	* Manufactured by Panasonic	JPEG recording : Manual REC / Alarm REC (Pre/Post) /
	(SD speed class 4 or higher)	Backup upon network failure Compatible
	* Use the SD memory card that complies with UHS-1 (Ultra High Speed-1) in the case of SD Speed Class 10.	SD (SDHC/SDXC) card: Panasonic
		2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB*, 64GB** model
		*SDHC card, ** SDXC card (except miniSD card and microSD card)
	Employment of two SD cards	Dual Recording for Redundancy
		Series Recording for long time
	Cellular Phone Compatibility	JPEG image, AUX control (by access level)
	Mobile Terminal Compatibility	iPad, iPhone, iPod touch (iOS 4.2.1 or later), Android™ Terminal
Alarm	Alarm Source	3 terminals input, VMD, Command alarm, Audio detection alarm
	Alarm Actions	SDXC/SDHC/SD memory recording, E-mail notification, HTTP alarm notification
		Indication on browser, FTP image transfer, Panasonic protocol output
	Alarm Log	With SDXC/SDHC/SD memory card :
		Up to 50,000 logs for each SD memory card
	Schedule	Alarm / VMD / Access permission / H.264 recording / Scene file
Input/	Monitor Output	VBS: 1.0 V [p-p]/75 Ω, NTSC / PAL composite,
Output	(for adjustment)	ø3.5mm mini jack MONITOR OUT conversion plug included
	Microphone/Line Input	MIC IN and Line IN are selectable. ø3.5 mm monaural mini jack
		(monaural input) (Applicable microphone: Plug-in power type)
		Supply voltage: 2.5 V ±0.5 V Input impedance: Approx. 2 kΩ (unbalanced)
	Audio Output	ø3.5 mm stereo mini jack (monaural output) Output impedance: Approx. 600 Ω (unbalanced)
	External I/O Terminals	ALARM IN 1/DAY/NIGHT IN, ALARM IN 2/ALARM OUT, ALARM IN 3/AUX OUT
General	Safety	UL (UL60950-1), C-UL (CAN/CSA C22.2 No.60950-1), CE, IEC60950-1
	EMS	FCC (Part15 ClassA), ICES003 ClassA, EN55022 ClassB, EN55024
	Power Source and	When IR LED is ON
	Power Consumption	WV-SFN631L
		DC power supply: 12 V DC/760 mA/Approx. 9.1 W
		PoE Device: 48 V DC/240 mA/Approx. 11.1 W (Class 0 device)
		WV-SFN611L
		DC power supply: 12 V DC/690 mA/Approx. 8.2 W
		PoE Device: 48 V DC/200 mA/Approx. 9.4 W (Class 0 device)
		* ONLY CONNECT 12 V DC CLASS 2 POWER SUPPLY.
	Ambient Operating Temperature	-10°C ~ +50°C (14 °F ~ 122 °F)
	Ambient Operating Humidity	20 ~ 90 % (no condensation)
	Dimensions	ø129.5 mm x 101 mm (H) {ø5-3/32 inches x 3-31/32 inches (H)}
		Dome radius 40 mm {1-9/16 inches}
	Mass (approx.)	Approx. 0.59kg {1.30 lbs}

### **Part Names and Functions**



### **Appearance**



- Trademarks and registered trademarks

   Microsoft, and Windows are registered trademarks of Microsoft Corporation in the U.S. and other countries.
- iPad, iPhone and iPod touch are registered trademarks of Apple Inc.
   Android is a trademark of Google Inc.
- UniPhier is a registered trademark of Panasonic Corporation.
- Unifine is a registered tradellar on Fatasonic Corporation.
   "I-PRO SmartHD" logo is trademark or registered trademark of Panasonic Corporation.
   ONVIF and the ONVIF logo are trademarks of ONVIF Inc.
- Important

   Safety Precaution: Carefully read the Important Information, Installation Guide and operating instructions before using this product.
- Panasonic cannot be responsible for the performance of the network and/or other manufacturers' products used on the network.
- Masses and dimensions are approximate. Specifications are subject to change without notice.

**DISTRIBUTED BY:** 



http://security.panasonic.com http://www.facebook.com/PanasonicNetworkCamera



<sup>\*1</sup> Converted value \*2 Super Dynamic function is automatically set of on 60fps mode.

\*3 Refer to "Notes on Windows Vista® / Windows® 7 / Windows® 8\* on the provided CD-ROM for further information about system requirements for a PC and precautions when using Microsoft® Windows® 8 or Microsoft® Windows® 7 or Microsoft® Windows Vista®.

\*4 Transmission for 4 streams can be individually set.